

# REPORT

## 70 Series



**finder**<sup>®</sup>  
SWITCH TO THE FUTURE



## Electronic voltage monitoring relay for three-phase applications

### Type 70.42

Multifunctional type, providing the flexibility of monitoring Undervoltage, Overvoltage, Window Mode, Phase rotation, Phase loss, Asymmetry and Neutral loss.

Approvals (according to type)



### Features

- 2 CO relay output, 8 A
- Positive safety logic - Make output contact opens if the relay detects an error
- All functions and values can be easily adjusted by the selector and trimmer on front face
- "Blade + cross" – both flat blade and cross head screw drivers can be used to adjust the regulators and the function selector
- Colored LEDs for clear & immediate visual indication
- Modular housing, 35 mm wide
- 35 mm rail (EN 60715) mount

## Voltage monitoring relays

Type	70.11	70.31	70.41	70.42
Nominal system voltage V AC (50/60 Hz)	Single-phase 220...240 V AC	Three-phase 380...415 V AC	Three-phase 380...415 V AC	Three-phase 380...415 V AC
Voltage detection level range	170...270 V	300...480 V	300...480 V	300...480 V
Neutral	—	without Neutro	with/without Neutral	with Neutral
Contact configuration	1 CO (SPDT)	1 CO (SPDT)	1 CO (SPDT)	1 CO (DPDT)
Voltage fault memory	selectable	selectable	—	selectable
Trip delay time	(0.5...60 s) adjustable	(0.5...60 s) adjustable	(0.5...60 s) adjustable	(0.5...60 s) adjustable
Dimension (wide, deep)	17.5 x 60 mm	35 x 60 mm	35 x 60 mm	35 x 60 mm
Function	Undervoltage	Undervoltage	—	Undervoltage
	Overtoltage	Overtoltage	—	Overtoltage
	Window mode	Window mode	Window mode	Window mode
	—	Phase loss	Phase loss	Phase loss
	—	Phase rotation	Phase rotation	Phase rotation
	—	—	Asymmetry	Asymmetry
—	—	Neutral loss	Neutral loss	

## Phase failure relays

Type	70.61	70.62
Nominal system voltage V AC (50/60 Hz)	Three-phase 208...480 V AC	Three-phase 208...480 V AC
Voltage detection level range	—	—
Neutral	—	—
Contact configuration	1 CO (SPDT)	2 CO (DPDT)
Voltage fault memory	—	—
Trip delay time	0.5 s fixed	0.5 s fixed
Dimension (wide, deep)	17.5 x 60 mm	22.5 x 100 mm
Function	Phase loss	Phase loss
	Phase rotation	Phase rotation

FINDER reserves the right to alter characteristics at any time without notice. FINDER assumes no liability for damage to persons or property, caused as a result of the incorrect use or application of its products.